



Fenix E12 Flashlight

The Fenix E12 Flashlight turns small size into go-anywhere, functional lighting. A single AA battery kicks out 130 lumens with 88-meter beam distance and 22 hours runtime on low mode. The tail tap switch controls all functions of this 90mm-long light: fully press the tail switch for constant-on, tap it for output selection and fully press it again to turn it off.




E12

Max 130 Lumens

User manual

Illuminate Your Adventure



Technical Parameters

ANSI/NEMA FL 1		High	Mid	Low
OUTPUT		130 Lumens	50 Lumens	8 Lumens
RUNTIME	Ni-MH Battery	1h30min	6h30min	40h
	Alkaline Battery	1h	3h30min	22h
DISTANCE		88m (Max)		
INTENSITY		1936cd (Max)		
IMPACT RESISTANT		1m		
WATERPROOF		IPX-8, underwater 2m		
ACCESSORIES		Lanyard, spare O-ring		

Note: The above-mentioned parameters (lab tested by Fenix using 2500mAh Ni-MH battery and the included Alkaline battery) are approximate and may vary between flashlights, batteries and environments.

- Uses Cree XP-E2 LED with a lifespan of 50000 hours
- Uses one AA (Ni-MH, Alkaline) battery
- 90mm (Length) * 19mm (Diameter)
- 28.5-gram weight (excluding the battery)
- Digitally regulated output - maintains constant brightness
- Reverse polarity protection guards against improper battery installation
- Tail tap switch for on/off and output selection
- Made of durable aircraft-grade aluminum
- Premium Type III hard-anodized anti-abrasive finish
- High-efficiency total reflection lens

Operation

ON/OFF

Press the tail switch to turn on the light on Low output and lock it. Another complete press on the switch turns it off.

Output selection

When the light is on, tap the tail switch to cycle the brightness level in the order of Low>Mid>High.

Battery Specifications

Type	Dimensions	Nominal Voltage	Usability	
NiMH Battery	AA	1.2V	Recommended	✓
Alkaline Battery	AA	1.5V	Usable	✓
Non-rechargeable Battery (3.6V)	AA	1.5V	Usable	✓
Rechargeable Battery (Li-ion)	14500	3.7V	Banned	✗

*Please do not use the banned batteries, or it may cause damages to the flashlight.

Battery Replacement

Unscrew the light head to put in the battery with the anode (+) toward the light head, Align the threads and screw the tail cap on to test.

Usage and Maintenance

- Please don't disassemble the sealed head, doing so can cause damage to the flashlight and will void the warranty.
 - High-power light should use battery with high current discharge capability; we suggest using high-performance Ni-MH rechargeable battery to increase the runtime of this high-intensity light.
 - Please take out the battery if the flashlight will not be used for a long time, or it may cause damage from electrolyte leakage or battery explosion.
 - The O-ring may be worn out after using for a long time. If it happens, please replace the O-ring with a new one to keep the light properly sealed against water.
 - Please clean the contacts of your light from time to time, especially if the light flickers or doesn't light up. There may be several reasons for a flickering or not working light:
Reason A: The battery needs replacing.
Solution: Replace the battery (Please confirm the correct installation of anode and cathode).
Reason B: The threads, PCB board contact or other contacts are dirty.
Solution: Clean the contact points with an alcohol soaked cotton swab.
- If the above methods don't work, please contact the distributors and refer to the warranty policy.

Product Warranty

We will replace products afflicted with manufacturing defects within 15 days of purchase and repair a light free of charge within 24 months of purchase if problems develop with normal use; if repair is required after 24 months from the date of purchase, we will charge for parts. The total repair fee is dictated by the cost of the replaced materials.

Product Registration

We kindly suggest that you register your product on the official website of Fenixlight Limited (www.fenixlight.com). You'll receive an extra six months of warranty coverage once you have successfully registered. By participating in an optional customer survey, you are entered in a drawing for free Fenix products.

Warning

E12 is a high-intensity lighting device capable of causing eye damage. Avoid shining the light directly into the eyes.