







Fenix™ E11

Fenix E11 is a mini high-intensity flashlight specially made for the outdoor sports. By twisting the light head, you can select between the two brightness levels rapidly. It combines the different needs of brightness and runtime reasonably. Plus with the advanced constant brightness technology and waterproofing to the IPX-8 Standard, the portable, compact and reliable E11 ensures you an easy and happy outdoor life.

Technical Parameters

ANSI/FSC	High	Low
 OUTPUT	105 LUMENS	32 LUMENS
 RUNTIME	1h 50min	8h 23min
 DISTANCE	72m	
 INTENSITY	1279cd	
 IMPACT RESISTANT	1m	
 WATERPROOF	IPX-8, underwater 2m	
EXTRA FUNCTION		
ACCESSORIES	Lanyard, spare o-ring and spare rubber switch boot	

- ⊙ Uses Cree XP-E LED with a lifespan of 50000 hours
- ⊙ Uses one 1.5V AA (Ni-MH, Alkaline) battery
- ⊙ 97mm (Length) * 19mm (Diameter)

- ⦿ 32-gram weight (excluding the battery)
- ⦿ Digitally regulated output - maintains constant brightness
- ⦿ Reverse polarity protection, to protect from improper battery installation
- ⦿ Tactical tail switch with momentary-on function
- ⦿ Made of durable aircraft-grade aluminum
- ⦿ Premium Type III hard-anodized anti-abrasive finish
- ⦿ High-efficiency total reflection lens

Note: The above-mentioned parameters (tested by 2500mAh Ni-MH battery in the lab) are approximate and may vary between flashlights, batteries and environments.

Operation Instruction

Press the tail switch lightly to activate the light. Press the switch completely to turn on the light and lock it. Another complete press on the switch can turn it off.

To screw the head or unscrew the head can select between the high brightness level and the low brightness level.

Battery Specifications

Type	Dimensions	Nominal voltage	Usability	
Ni-MH battery	AA	1.2V	Recommended	✓
Alkaline battery	AA	1.5V	Usable	✓
Non-rechargeable Battery (Lithium)	AA	1.5V	Usable	✓
Rechargeable Battery (Li-ion)	14500	3.7V	Banned	✗

Battery Replacement

Unscrew the light head to put in the battery with the anode (+) toward the light head, screw the light head back on to test.

Usage and Maintenance

- ⦿ Please don't disassemble the sealed head, doing so can cause damage to the flashlight and will void the warranty.
- ⦿ High-power light should use battery with high current discharge capability; We suggest using **high-performance Ni-MH rechargeable battery to increase the runtime of this high-intensity light.**
- ⦿ Please use battery of high quality, and take out the battery if the flashlight will not be used for a long time, or it may cause damage from electrolyte leakage or battery explosion.
- ⦿ The o-ring may be worn out after using for a long time. If it happens, please replace the o-ring with a new one to keep the light properly sealed against water.
- ⦿ Please clean the contacts of your light from time to time, especially if the light flickers or doesn't light up. There may be several reasons for a flickering or not working light:

Reason A: The battery needs replacing.

Solution: Replace the battery (Please confirm the correct installation of anode and cathode).

Reason B: The threads, PCB board contact or other contacts are dirty.

Solution: Clean the contact points with an alcohol soaked cotton swab.

If the above methods don't work, please contact the distributors and refer to the warranty policy.

Notice: The routine cleaning video can be watched and downloaded through Fenix official website, please log onto the service channel->'maintenance for light'.

Product Warranty

We will replace products afflicted with manufacturing defects within 15 days of purchase and repair a light free of charge within 24 months of purchase if problems develop with normal use; if repair is required after 24 months from the date of purchase, we will charge for parts. The total repair fee is dictated by the cost of the replaced materials.

Warranty Card Registration

We kindly suggest that you register your guarantee card on the official website for Fenixlight Limited. You can get an extra six-month warranty period once you have successfully registered. What's more, you could take part in the lottery of questionnaire at the same time.

Warning

E11 is a high-intensity lighting device and capable of causing eye damage, avoid shining the light directly into the eyes.